

Table of Contents

4.	LOOP _____	3
4.1	INTRODUCTION _____	3
4.2	LOOP ADMINISTRATIVE SECTION _____	4
1.	PON - Purchase Order Number _____	4
2.	VER – Version Identification _____	5
3.	AN - Account Number _____	6
4.	ATN – Account Telephone Number _____	7
5.	LQTY - Loop Quantity _____	8
6.	PG_of_ - Page _ of _ _____	9
4.3	LOOP SERVICE DETAILS SECTION _____	10
7.	LOCNUM – Location Number _____	10
8.	LNUM – Line Number _____	11
9.	LNA - Line Activity _____	12
10.	SLTN – Shared Line Telephone Number _____	14
11.	LMT – Loop Modification Type _____	15
12.	BTRL - Bridged Tap Removal Location _____	16
13.	CKR - Customer Circuit Reference _____	17
14.	CMA – Commingling Arrangement _____	18
15.	TSP - Telecommunication Service Priority _____	19
16.	TNT – Test and Tag Requested _____	20
17.	ISR – Installation Service Requested _____	21
18.	DRT – Data Rate Testing _____	22
19.	SAN - Subscriber Authorization Number _____	23
20.	ECCKT - Exchange Company Circuit ID _____	24
21.	RL – Reuse Loop _____	25
22.	OECCKT – Out Exchange Company Circuit ID _____	26
23.	RESID – Response Identifier _____	28
24.	CFA - Connecting Facility Assignment _____	29
25.	CCEA – Cross Connect Equipment Assignment _____	31
26.	RECCKT - Related Exchange Company Circuit ID _____	32
27.	VPID – Virtual Path Indicator _____	33
28.	VPI – Virtual Path Identifier _____	34
29.	VCI – Virtual Circuit Identifier _____	35
30.	UDSPEED – Upstream and Downstream Speed _____	36
31.	SYSTEM ID - System Identification _____	37
32.	CTI - Connection Type Indicator _____	38
33.	CABLE ID - Cable Identification _____	39
34.	CBCID – Cross Box Cable Identification _____	40
35.	CHAN/PAIR - Channel/Pair _____	41
36.	RELAY RACK – Relay Rack _____	42
37.	SHELF – Shelf _____	44
38.	SLOT – Slot _____	45
39.	SPORT - Slot Port _____	46
40.	UNIT – Unit _____	47
41.	JK CODE - Jack Code _____	48
42.	JK NUM - Jack Number _____	49
43.	JK POS - Jack Position _____	50
44.	JR - Jack Request _____	51
45.	IWT - Inside Wire Type _____	52

Loop – Section 4

46.	NIDR - NID Request _____	53
47.	IWJK - Inside Wire Jack Code _____	54
48.	IWJQ - Inside Wire Jack Quantity _____	55
49.	DISC NBR - Disconnect Telephone Number _____	56
50.	TERS - Terminal Numbers _____	57
51.	TC OPT - Transfer of Call Options _____	58
52.	TC TO PRI - Transfer of Calls To Primary Number _____	59
53.	TC TO SEC - Transfer of Calls To Secondary Number _____	60
54.	TCID - Transfer of Calls To Identifier _____	61
55.	TC NAME - Transfer of Calls To Name _____	62
56.	TC PER - Transfer of Calls Period _____	63
57.	LEAN - Line Existing Account Number _____	64
58.	LEATN – Line Existing Account Telephone Number _____	65
59.	REMARKS - Remarks _____	66
60.	CLEC TEL NO – CLEC Telephone Number _____	67
61.	SOE REMARKS – SOE Remarks _____	68

4. LOOP

4.1 INTRODUCTION

1. This section describes the Loop Service (LS) Form entries. The LS Form must always be associated with an LSR Form and may be associated with an EU Form, which contains administrative and bill detail necessary for the provisioning of this request. The field entries contained within the LS Form are to be provided by the customer.

4.2 LOOP ADMINISTRATIVE SECTION

1. PON - Purchase Order Number

Identifies the customer's unique purchase order or requisition number that authorizes the issuance of this request or supplement.

INTERFACE	Field Name
IRES	PON
FTP	PON

NOTE 1: The purchase order number can not be reused.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E	A	R	R	R	R	R	R	P	P	P	R
Q											

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 16 alphanumeric characters

EXAMPLE:

8	2	4	Z	9											
---	---	---	---	---	--	--	--	--	--	--	--	--	--	--	--

2. VER – Version Identification

Identifies the customer's version number.

Interface	Field Name
IRES	VER
FTP	Not applicable

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		R	R	R	R	R	P	P	P	P	R
Q	A										

NOTE 1: The VER is auto-populated by IRES.

NOTE 2: IRES will increment the VER field by 1 when a SUP is submitted.

DATA CHARACTERISTICS: 2 numeric characters

EXAMPLES:

1	2
---	---

8	
---	--

3. AN - Account Number

Identifies the main account number assigned by the NSP.

Interface	Field Name
IRES	Not Applicable
FTP	Not Applicable

NOTE 1: This field is the Sprint LTD end users main telephone number assigned by Sprint LTD and represents an account that has not been migrated to another customer.

NOTE 2: This field is used to recognize the main telephone number that must be preordered in order to obtain all other associated telephone numbers.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E	A	C	P	P	P	R	P	P	P	P	P
Q											

NOTE 1: Field is only supported for manual processing.

NOTE 2: When REQ TYPE = A and 2nd TOS = R, this field is required, otherwise prohibited.

DATA CHARACTERISTICS: 10 numeric characters (excluding 2 preprinted hyphens)

EXAMPLE:

2	0	1
---	---	---

 -

5	5	5
---	---	---

 -

1	2	1	2
---	---	---	---

4. ATN – Account Telephone Number

Identifies the account telephone number assigned by the NSP.

Interface	Field Name
IRES	TEL NO
FTP	TN

NOTE 1: This field describes all telephone numbers associated with the AN field.

NOTE 2: All numbers requesting migration must be supplied.

NOTE 3: When processing manually, each telephone number must be listed on a separate form.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		P	P	P	P	R	P	P	P	P	P
Q	A										

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

NOTE 2: Field will be auto-populated in IRES based on preorder information.

DATA CHARACTERISTICS: 10 numeric characters (excluding 2 preprinted hyphens)

EXAMPLE: | 2 | 0 | 1 | - | 5 | 5 | 5 | - | 1 | 2 | 1 | 2 |

5. LQTY - Loop Quantity

Identifies the quantity of loops involved in this service request.

Interface	Field Name
IRES	LOOP QTY
FTP	LQTY

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		R	R	R	R	R	P	P	P	P	R
Q	A										

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: Depending on REQ/ACT combination, field may be auto-populated in IRES.

DATA CHARACTERISTICS: 4 numeric characters

EXAMPLE:

			1
--	--	--	---

6. PG_of_ - Page _ of _

Identifies the page number and total number of pages contained in this request.

Interface	Field Name
IRES	Not Applicable
FTP	Not Applicable

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		R	R	R	R	R	P	P	P	P	R
Q	A										

DATA CHARACTERISTICS: 4 numeric characters

EXAMPLE: PG 1 of 2

4.3 LOOP SERVICE DETAILS SECTION

7. LOCNUM – Location Number

Identifies the service location number for the service requested

USAGE: This field is not supported by Sprint LTD.

8. LNUM – Line Number

Identifies the line or trunk as a unique number and each additional occurrence as a unique number.

Interface	Field Name
IRES	LNUM
FTP	Not Applicable

NOTE 1: The LNUM is customer assigned for manual requests and is returned on the Local Response (LR) Form to the ordering customer.

NOTE 2: Once LNUM is assigned manually, it may be changed by Sprint LTD.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		R	R	R	R	R	P	P	P	P	R
Q	A										

NOTE 1: Field is auto-populated in IRES based on telephone numbers/circuits preordered.

DATA CHARACTERISTICS: 4 numeric characters

EXAMPLE:

0	0	0	1
---	---	---	---

9. LNA - Line Activity

Identifies the activity involved at the line level.

Interface	Field Name
IRES	LNA
FTP	LLNA

VALID ENTRIES:

- B = Restore
- C = Change an existing account, e.g., rearrangement, partial disconnect or addition
- D = Disconnection
- H = Short term
- L = Seasonal
- M = Inside move of the physical termination within a building
- N = New installation and/or account
- P = Pre-Qualification
- R = Record activity is for ordering administrative changes
- S = Suspend
- T = Outside move of end user location
- V = Conversion of service to new LSP as specified
- W = Conversion as is
- X = Telephone number change
- Y = Deny

NOTE 1: “B”, “H”, “L”, “M”, “R”, “P”, “S”, “X” and “Y” are not supported by Sprint LTD.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		R	R	R	R	R	P	P	P	P	R
Q	A										

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: When ACT=V, valid LNA values are “N” and “V.”

NOTE 3: When ACT=D, valid LNA value is “D.”

NOTE 4: When ACT=N, valid LNA value is “N.”

NOTE 5: When ACT=C, valid LNA value is “C.”

NOTE 6: When ACT=T, valid LNA value is “T.”

NOTE 7: When ACT=P, valid LNA value is “P.”

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE:

N

10. SLTN – Shared Line Telephone Number

Identifies the end user telephone number(s) for line sharing or line splitting.

Interface	Field Name
IRES	CKR
FTP	CKR

NOTE 1: IRES and FTP use the CKR field to identify the line sharing telephone number, however this is not industry compliant.

NOTE 2: For manual processing, SLTN field will be utilized.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E											
Q	A	C	C	C	P	P	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: Required when the second position of the TOS field on the LSR Form is “R” and the LNA field is “N”.

DATA CHARACTERISTICS: 10 numeric characters (including 2 pre-populated hyphens)

EXAMPLE:

9	1	3	-	1	1	1	-	1	1	1	1								
---	---	---	---	---	---	---	---	---	---	---	---	--	--	--	--	--	--	--	--

11. LMT – Loop Modification Type

Identifies the loop changes involved in this service request.

Interface	Field Name
IRES	CONDITIONING REMARKS
FTP	CNDRMK

USAGE: Refer to fields listed above in Section 2 - LSR

12. BTRL - Bridged Tap Removal Location

Identifies the location of the bridged tap to be removed from the loop.

Interface	Field Name
IRES	CONDITIONING REMARKS
FTP	CNDRMK

USAGE: Refer to fields listed above in Section 2 – LSR.

13. CKR - Customer Circuit Reference

Identifies the circuit number or sequential range of circuit numbers assigned by the customer.

Interface	Field Name
IRES	CKR
FTP	CKR

NOTE 1: CKR is used by the customer as a cross-reference to the provider circuit ID and in many cases to identify the customer’s end to end service.

NOTE 2: Sprint LTD uses this field to designate end users telephone number for line sharing.

NOTE 3: CKR appears in other sections and is supported in the manner industry intended.

USAGE: This field is not supported by Sprint LTD.

14. CMA – Commingling Arrangement

Identifies the billing configuration in a commingled service arrangement for same bandwidth segments.

USAGE: This field is not supported by Sprint LTD.

15. TSP - Telecommunication Service Priority

Indicates the provisioning and restoration priority as defined under the TSP Service Vendor Handbook.

Interface	Field Name
IRES	TSP
FTP	TSP

NOTE 1: These codes are assigned by the TSP Program Office.

VALID ENTRIES:

- Nine character TSP control identifier
- One character provisioning priority level (E, 0-5)
- One digit restoration priority level (0-5)

NOTE 1: A TSP code ending in “00” indicates “revocation”, the removal of a previously assigned TSP code.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		O	O	O	O	O	P	P	P	P	P
Q	A	O	O	O	O	O	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

DATA CHARACTERISTICS: 30 alphanumeric characters (including 1 hyphen)

EXAMPLE: | T | S | P | 1 | 2 | 3 | 4 | 5 | C | - | E | 1 |

16. TNT – Test and Tag Requested

Identifies the customer is requesting additional testing and tagging beyond that which is included with the product ordered.

Interface	Field Name
IRES	LOOPTAG/CTEST
FTP	LOOPTAG/CTEST

USAGE: Refer to fields listed above in Section 2 – LSR.

17. ISR – Installation Service Requested

Identifies that the customer is requesting a provider technician to assist the end user with installation and configuration of on-site equipment.

USAGE: This field is not supported by Sprint LTD.

18. DRT – Data Rate Testing

Identifies the requested data rate at the time of turn-up for digital loop requests.

USAGE: This field is not supported by Sprint LTD.

19. SAN - Subscriber Authorization Number

Identifies a number equivalent to the end user purchase order number.

USAGE: This field is not supported by Sprint LTD.

20. ECCKT - Exchange Company Circuit ID

Identifies a provider’s circuit identification.

Interface	Field Name
IRES	ECCKT
FTP	ECCKT

- NOTE 1:** The format of the field is defined by the provider.
- NOTE 2:** All components within the ID should be delimited by periods.
- NOTE 3:** The layout of the field may be defined by the COMMON LANGUAGE standards.
- NOTE 4:** When a component of CLT, CLS and CLF is purposely omitted, the component should still be delimited and compressed to eliminate any spaces.
- NOTE 5:** If all positions in a component of CLT, CLS and CLF are not populated, the component should be compressed to eliminate any spaces.

VALID ENTRIES:

SERIAL NUMBER FORMAT:

Prefix/service code and modifier/serial number/suffix code/AP code/segment name (if applicable)

This format may be up to 27 characters in length.

EXAMPLE: 77.UCFS.123456..CTRL

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	A	P	R	R	R	P	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

DATA CHARACTERISTICS: 41 alphanumeric characters

21. RL – Reuse Loop

Identifies the customers desire to reuse the loop from an existing service arrangement for this request.

USAGE: This field is not supported by Sprint LTD.

22. OECCKT – Out Exchange Company Circuit ID

Identifies the circuit identification that was previously provided to the old LSP/NSP-Switch by the NSP-Loop.

Interface	Field Name
IRES	OECCKT
FTP	Not Applicable

NOTE 1: The format of the field is defined by the provider.

NOTE 2: All components within the ID should be delimited by either virgules or periods.

NOTE 3: The layout of the field may be defined by the COMMON LANGUAGE standards.

NOTE 4: When a component of CLT, CLS and CLF is purposely omitted, the component should still be delimited and compressed to eliminate any spaces.

NOTE 5: If all positions in a component of CLT, CLS and CLF are not populated, the component should be compressed to eliminate any spaces.

VALID ENTRIES:

SERIAL NUMBER FORMAT:

Prefix/service code and modifier/serial number/suffix code/AP code/segment name (if applicable)

This format may be up to 27 characters in length.

EXAMPLE: 77.UCFS.123456..CTRL

USAGE: This field is conditional.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		P	P	P	O	P	P	P	P	P	P
Q	A	P	P	P	O	P	P	P	P	P	P

NOTE 1: When REQ/ACT A/T and the MCSI=Y, then field will be auto-populated in IRES.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

DATA CHARACTERISTICS: 41 alphanumeric characters

23. RESID – Response Identifier

Identifies the response number assigned by the provider to relate associated transactions.

USAGE: This field is not supported by Sprint LTD.

24. CFA - Connecting Facility Assignment

Identifies the provider carrier system and channel to be used.

Interface	Field Name
IRES	CFA
FTP	CFA

NOTE 1: The format and structure of this field is defined by ANSI in document T1.238, Identification of Telecommunication Facilities for the North American Telecommunications System. The Facility Identifier consists of the following elements:

1. **Facility Designation** – A code that, for a specific type of facility, uniquely identifies a path between two network nodes (variable length, 1-5 alphanumeric characters).
2. **Facility Type** – A code that describes a type of facility when it is other than a single baseband channel on cable. Valid entries are outlined in Telcordia Technologies document BR-795-450-100 (variable length, 1-6 alphanumeric characters).
3. **Channel/Pair/Time Slot** – A code that identifies a specific assignable portion of a facility (variable length, 1-5 alphanumeric characters).
4. **Location A** – A standardized code that uniquely identifies the location of facility terminal A, which has the lower in alphanumeric sequence of the two facility location codes. Valid values are outlined in Telcordia Technologies document BR-795-100-100 (8 or 11 alphanumeric characters).
5. **Location Z** – A standardized code that uniquely identifies the location of facility terminal Z, which has the higher in alphanumeric sequence of the two facility location codes. Valid values are outlined in Telcordia Technologies document BR-795-100-100 (8 or 11 alphanumeric characters).

NOTE 1: Either virgules (/) or periods (.) are used consistently as delimiters to separate all elements of the CFA.

NOTE 2: All element entries of the CFA are left justified with no trailing spaces.

NOTE 3: Applicable when utilizing Hi-Cap facilities and the customer has assignment control.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	A	O	O	O	O	O	P	P	P	P	O

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 42 alphanumeric characters

EXAMPLES: | 1 | 0 | 1 | / | T | 1 | / | 3 | / | B | S | T | N | M | A | G | T | C | G | O | / |

| B | S | T | N | M | A | M | T | C | G | O | | | | | | | | | | | |

| 1 | 0 | 1 | . | T | 1 | . | 3 | . | B | S | T | N | M | A | G | T | C | G | O | . |

| B | S | T | N | M | A | M | T | C | G | O | | | | | | | | | | | |

25. CCEA – Cross Connect Equipment Assignment

Identifies the physical point of termination at a collocation arrangement.

USAGE: This field is supported by Sprint LTD.

26. RECCKT - Related Exchange Company Circuit ID

Identifies the provider's related physical circuit ID against which the virtual circuit activity is requested.

USAGE: This field is not supported by Sprint LTD.

27. VPID – Virtual Path Indicator

Identifies the logical connection location and quality of service for the virtual path requested.

USAGE: This field is not supported by Sprint LTD.

28. VPI – Virtual Path Identifier

Identifies the logical connection address for the virtual path requested.

USAGE: This field is not supported by Sprint LTD.

29. VCI – Virtual Circuit Identifier

Identifies the logical connection address between the provider's switch and the circuit for the virtual circuit requested.

USAGE: This field is not supported by Sprint LTD.

30. UDSPEED – Upstream and Downstream Speed

Identifies the upstream and downstream speed of the virtual circuit.

USAGE: This field is not supported by Sprint LTD.

31. SYSTEM ID - System Identification

Identifies the customer's system to be used in a collocation arrangement.

USAGE: This field is not supported by Sprint LTD.

32. CTI - Connection Type Indicator

Identifies the configuration of the facility connection assignment.

Interface	Field Name
IRES	DATA TYPE
FTP	DT*TP1, DT*TP2, DT*TP3, DT*TP4

NOTE 1: This information is provided when the customer has assignment control.

NOTE 2: Up to four iterations may be requested.

NOTE 3: When the CTI field is populated, for each occurrence of CTI, there must be a matching occurrence of CABLE ID and CHAN/PAIR or CBCID and CHAN/PAIR.

VALID ENTRIES:

- VD = Voice and Data
- V = Voice
- D = Data

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		C	C	O	C	P	P	P	P	P	P
Q	A	C	C	O	C	P	P	P	P	P	P

NOTE 1: Required when second position of the TOS field on the LSR Form is “R” and the corresponding CABLE ID and CHAN PAIR fields are populated, otherwise prohibited.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

NOTE 3: When the ACT = T and MCSI=N, this field is prohibited for 2nd, 3rd and 4th iterations.

NOTE 4: If there is a 2nd iteration, the 1st iteration must be present. If there is a 4th iteration, 1st, 2nd and 3rd iterations must be present.

DATA CHARACTERISTICS: 2 alpha character

EXAMPLE: A

33. CABLE ID - Cable Identification

Identifies the provider's cable to be connected to the customer's equipment in a central office location.

Interface	Field Name
IRES	CABLE ID
FTP	CABLEID1, CABLEID2, CABLEID3, CABLEID4

NOTE 1: Applicable when the customer has assignment control.

NOTE2: Up to four iterations may be requested.

NOTE 3: An iteration will consist of cable id, channel pair and may or may not consist of CTI.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		R	R	O	C	R	P	P	P	P	P
Q	A										

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: First iteration of Cable ID is required.

NOTE 3: If NCI field begins with 04, the second iteration of Cable ID is required.

NOTE 4: When the ACT = 'T' and MCSI=N, this field is prohibited for the 2nd, 3rd and 4th iterations.

NOTE 5: If ACT=N and 2nd TOS=R, the second iteration of cable ID is required.

NOTE 6: If there is a 2nd iteration, the 1st iteration must be present. If there is a 4th iteration, 1st, 2nd and 3rd iterations must be present.

DATA CHARACTERISTICS: 5 alphanumeric characters

EXAMPLE: | X | X | X | 0 | 1 |

34. CBCID – Cross Box Cable Identification

Identifies the provider's cable to be connected to the customer's terminal in a field location.

USAGE: This field is not supported by Sprint LTD.

35. CHAN/PAIR - Channel/Pair

Identifies the specific channel or pair within the provider's cable to be used for connection.

Interface	Field Name
IRES	CHAN PAIR
FTP	CHANPAIR1, CHANPAIR2, CHANPAIR3, CHANPAIR4

NOTE 1: Applicable when the customer has assignment control.

NOTE 2: Up to four iterations may be requested when the CABLE ID field is populated; however, only one iteration may be provided per CABLE ID.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		R	R	O	C	R	P	P	P	P	P
Q	A										

NOTE 1: Required when the associated CABLE ID field is populated, otherwise prohibited.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

NOTE 3: First iteration of Chan Pair is required.

NOTE 4: If NCI field begins with 04, the second iteration of Chan Pair is required.

NOTE 5: When the ACT = T and MCSI=N, this field is prohibited for the 2nd, 3rd and 4th iterations.

NOTE 6: If ACT=N and 2nd TOS=R, the second iteration of chan pair is required.

NOTE 7: If there is a 2nd iteration, the 1st iteration must be present. If there is a 4th iteration, 1st, 2nd and 3rd iterations must be present.

DATA CHARACTERISTICS: 7 alphanumeric characters

EXAMPLE:

2	4					
---	---	--	--	--	--	--

36. RELAY RACK – Relay Rack

Identifies the bay/cabinet in a central office and may include the floor and aisle where the specific piece of equipment is located.

Interface	Field Name
IRES	RELAY RACK
FTP	RELAYRACK

NOTE 1: The format and structure of this field is defined by Telcordia Technologies practice BR 751-100-785. The Relay Rack consists of the following elements:

1. **Floor/Level** – Character positions one (1) and two (2) outline the Floor or Level value. This data element is a mnemonic code that consists of certain combinations of alpha, numeric and special characters. It defines a particular floor/level where frames are located. Valid entries are outlined in Telcordia Technologies document BR 751-100-785. (2 alphanumeric characters)
2. **Line-Up/Frame Function** – Character positions three (3) through seven (7) identify either a Line-Up or Frame Function. When this data element contains Line-Up data, it is a particular row of relay equipment in a central office. A Frame Function Code identifies the various frames, racks, bays and cabinets installed in a central office. Valid entries are outlined in Telcordia Technologies document BR 751-100-785. (1-5 alphanumeric characters)
3. **Bay Number** – Character positions eight (8) and nine (9) identify the Bay Number. This data element is a numeric code that identifies various bays or frames within a central office. Valid entries are outlined in Telcordia Technologies document BR 751-100-785. (2 numeric characters)
4. **Bay Designation** – Character position ten (10) identifies the Bay Designation. This data element is 1 character that identifies the Front, Back or marker group of the switching system. Valid entries are outlined in Telcordia Technologies document BR 751-100-785. (1 alpha character)

NOTE 2: Applicable when the customer has assignment control in a collocation arrangement.

NOTE 3: May be applicable when the customer has assignment control of the POTS line splitter in a line sharing or line splitting arrangement.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		O	O	O	O	O	P	P	P	P	P
Q	A	O	O	O	O	O	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 10 alphanumeric characters

EXAMPLE: | 0 | A | - | - | - | - | 3 | 0 | 2 | |

NOTE 1: The example indicates the Second Level below surface, Line-Up 3, Bay 2.

| 1 | 7 | | | 1 | 1 | 8 | 1 | 2 | F |

NOTE 1: The example indicates Floor 17, Line-Up 118, Bay 12, Front.

37. SHELF – Shelf

Identifies the number assigned to the shelf within the relay rack.

Interface	Field Name
IRES	SHELF
FTP	SHELF

NOTE 1: Applicable when the customer has assignment control in a collocation arrangement.

NOTE 2: May be applicable when the customer has assignment control of the POTS line splitter in a line sharing or line splitting arrangement.

USAGE: See the usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	A	O	O	O	O	O	P	P	P	P	P

NOTE 1: Optional when the RELAY RACK field is populated, otherwise prohibited.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

DATA CHARACTERISTICS: 6 alphanumeric characters

EXAMPLE:

2	0				
---	---	--	--	--	--

38. SLOT – Slot

Identifies the specific connection slot of the shelf to be used.

Interface	Field Name
IRES	SLOT
FTP	SLOT

NOTE 1: Applicable when the customer has assignment control in a collocation arrangement.

NOTE 2: May be applicable when the customer has assignment control of the POTS line splitter in a line sharing or line splitting arrangement.

USAGE: This field is conditional.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		O	O	O	O	O	P	P	P	P	P
Q	A	O	O	O	O	O	P	P	P	P	P

NOTE 1: Optional when the SHELF field is populated, otherwise prohibited.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

DATA CHARACTERISTICS: 4 alphanumeric characters

EXAMPLE:

0	7		
---	---	--	--

39. SPORT - Slot Port

Identifies the specific connection port of the slot to be used.

USAGE: This field is not supported by Sprint LTD.

40. UNIT – Unit

Identifies the number assigned to a panel, shelf or case within the customer's bay/cabinet indicated in the RELAY RACK field.

USAGE: This field is not supported by Sprint LTD.

41. JK CODE - Jack Code

Indicates the standard code for the particular registered or non-registered jack used to terminate the service.

USAGE: This field is not supported by Sprint LTD.

42. JK NUM - Jack Number

Identifies the number of the jack used on end user connections.

USAGE: This field is not supported by Sprint LTD.

43. JK POS - Jack Position

Identifies the position in the jack that a particular service will occupy.

USAGE: This field is not supported by Sprint LTD.

44. JR - Jack Request

Indicates a request for a new jack.

USAGE: This field is not supported by Sprint LTD.

45. IWT - Inside Wire Type

Identifies the type of inside wiring to be used.

USAGE: This field is not supported by Sprint LTD.

46. NIDR - NID Request

Indicates a request for a new Network Interface Device (NID).

Interface	Field Name
IRES	NIDR
FTP	NIDR

VALID ENTRIES:

Y = Yes

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		O	O	O	O	O	P	P	P	P	P
Q	A	O	O	O	O	O	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE:

47. IWJK - Inside Wire Jack Code

Indicates the standard code for the type of jack requested for inside wiring.

USAGE: This field is not supported by Sprint LTD.

48. IWJQ - Inside Wire Jack Quantity

Indicates the number of jacks requested for inside wiring.

USAGE: This field is not support by Sprint LTD.

49. DISC NBR - Disconnect Telephone Number

Identifies the end user telephone number to be disconnected.

Interface	Field Name
IRES	DISC NO
FTP	DISCNBR

USAGE: Refer to Section 3 - End User.

50. TERS - Terminal Numbers

Identifies a non-lead line in a multi-line hunt group or consecutive range of terminal numbers.

USAGE: This field is not supported by Sprint LTD.

51. TC OPT - Transfer of Call Options

Identifies the type of transfer of call option the end user has requested.

Interface	Field Name
IRES	TC OPT
FTP	TCOPT

USAGE: Refer to Section 3 – End User.

52. TC TO PRI - Transfer of Calls To Primary Number

Identifies the telephone number to which calls are to be referred.

Interface	Field Name
IRES	TC TO PRI
FTP	TCTOPRI

USAGE: Refer to Section 3 - End User.

53. TC TO SEC - Transfer of Calls To Secondary Number

Identifies the secondary telephone number to which calls are to be referred.

USAGE: This field is not supported by Sprint LTD.

54. TCID - Transfer of Calls To Identifier

Identifies the sequence of telephone numbers and names associated with split transfer of calls.

USAGE: This field is not supported by Sprint LTD.

55. TC NAME - Transfer of Calls To Name

Identifies the name(s) associated with TC TO PRI and TC TO SEC fields to which calls are to be referred when split transfer of calls is requested.

USAGE: This field is not supported by Sprint LTD.

56. TC PER - Transfer of Calls Period

Indicates the requested date that the transfer of calls, specified in the TC TO PRI field, is to be removed and the standard recorded announcement is to be provided.

Interface	Field Name
IRES	TC PER
FTP	TCPER

USAGE: Refer to Section 3 - End User Section.

57. LEAN - Line Existing Account Number

Identifies the end user's existing account number assigned by the current NSP and/or LSP.

USAGE: This field is not supported by Sprint LTD.

58. LEATN – Line Existing Account Telephone Number

Identifies the end user's existing account telephone number assigned by the old LSP.

USAGE: This field is not supported by Sprint LTD.

60. CLEC TEL NO – CLEC Telephone Number

Identifies a telephone number assigned to the end user by the CLEC.

Interface	Field Name
IRES	CLEC TEL NO
FTP	DTCINO

NOTE 1: This is Sprint LTD proprietary field.

NOTE 2: This is the telephone number owned and assigned by a facility based customer and is associated with a loop.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E		R	C	R	R	R	P	P	P	P	P
Q	A	R	C	R	R	R	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: Required when ACT = C and directory listing is to be amended, otherwise optional.

DATA CHARACTERISTICS: 10 numeric characters (excluding 2 preprinted hyphens)

EXAMPLE:

2	0	1
---	---	---

 -

5	5	5
---	---	---

 -

1	2	1	2
---	---	---	---

61. SOE REMARKS – SOE Remarks

Identifies information that is to be written directly to the service order (SOE).

Interface	Field Name
IRES	SOE REMARKS
FTP	Not Applicable

NOTE 1: This is Sprint LTD proprietary field.

NOTE 2: The purpose of this field is to allow users to provide information such as driving directions, can be reached numbers and rotary hunt sequences.

USAGE: See usage strip below.

ACTIVITIES											
REQ		N	C	D	T	V	W	S	B	L	P
	A	O	O	O	O	O	P	P	P	P	P

DATA CHARACTERISTICS: 50 alphanumeric characters

EXAMPLE: N | W | | C | O | R | N | E | R | | O | F | | 5 | T | H | | & | | S |
 | A | N | T | A | | F | E | | B | L | V | D | . | | B | E | H | I | N | D |
 | | T | H | E | | P | I | Z | Z | A | | S | H | O | P | | | | |