

Table of Contents

5.	NUMBER PORTABILITY _____	2
5.1	INTRODUCTION _____	2
5.2	NUMBER PORTABILITY ADMINISTRATIVE SECTION _____	3
1.	PON - Purchase Order Number _____	3
2.	VER – Version Identification _____	4
3.	AN - Account Number _____	5
4.	ATN - Account Telephone Number _____	6
5.	NPQTY - Number Portability Quantity _____	7
6.	PG_of_ - Page _ of _ _____	8
5.3	NUMBER PORTABILITY SERVICE DETAILS SECTION _____	9
7.	LOCNUM - Location Number _____	9
8.	LNUM - Line Number _____	10
9.	NPI - Number Portability Indicator _____	11
10.	LNA - Line Activity _____	12
11.	RL – Reuse Loop _____	14
12.	CKR - Customer Circuit Reference _____	15
13.	LRN - Location Routing Number _____	16
14.	TDT - Ten Digit Trigger _____	17
15.	ECCKT - Exchange Company Circuit ID _____	18
16.	OECCKT – Out Exchange Company Circuit ID _____	19
17.	PORTED NBR - Ported Telephone Number _____	20
18.	TNP - Total Number of Paths _____	21
19.	CFTN - Call Forward To Number _____	22
20.	NPT - Number Portability Type _____	23
21.	RTI - Route Index _____	24
22.	NPTG - Number Portability Trunk Group _____	25
23.	LSCP – Local Service Provider Change Prohibited _____	26
24.	BA - Blocking Activity _____	27
25.	BLOCK - Block _____	28
26.	FPI - Freeze PIC Indicator _____	29
27.	LPIC – IntraLATA Pre-subscription Indicator Code _____	30
28.	TC OPT - Transfer of Call Options _____	31
29.	TC TO PRI - Transfer of Calls To Primary Number _____	32
30.	TC TO SEC - Transfer of Calls To Secondary Number _____	33
31.	TCID - Transfer of Calls To Identifier _____	34
32.	TC NAME - Transfer of Calls To Name _____	35
33.	TC PER - Transfer of Calls Period _____	36
34.	LEAN - Line Existing Account Number _____	37
35.	LEATN - Line Existing Account Telephone Number _____	38
36.	REMARKS - Remarks _____	39
37.	SOE REMARKS – SOE Remarks _____	40

5. NUMBER PORTABILITY

5.1 INTRODUCTION

1. This section describes the Number Portability (NP) Form entries. The NP Form must always be associated with LSR and EU Forms which contain administrative and bill detail necessary for the provisioning of this request. The field entries contained within the NP Form are to be provided by the customer.
2. Sprint LTD does not support ranging. Each line number must be listed individually at the LNUM level.

5.2 NUMBER PORTABILITY ADMINISTRATIVE SECTION

1. PON - Purchase Order Number

Identifies the customer's unique purchase order or requisition number that authorizes the issuance of this request or supplement.

INTERFACE	Field Name
IRES	PON
FTP	PON

NOTE 1: The purchase order number can not be reused.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	R	P	P	P	P	P
	C/INP	P	P	P	P	R	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 16 alphanumeric characters

EXAMPLE:

8	2	4	Z	9											
---	---	---	---	---	--	--	--	--	--	--	--	--	--	--	--

2. VER – Version Identification

Identifies the customer’s version number.

Interface	Field Name
IRES	VER
FTP	Not applicable

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	R	P	P	P	P	P
	C/INP	P	P	P	P	R	P	P	P	P	P

NOTE 1: The VER is auto-populated by IRES.

NOTE 2: IRES will increment the VER field by 1 when a SUP is submitted.

DATA CHARACTERISTICS: 2 numeric characters

EXAMPLES: | 1 | 2 |

| 8 | |

3. AN - Account Number

Identifies the main account number assigned by the NSP.

Interface	Field Name
IRES	Not Applicable
FTP	Not Applicable

NOTE 1: This field is the Sprint LTD end users main telephone number assigned by Sprint LTD and represents an account that has not been migrated to another customer.

NOTE 2: This field is used to recognize the main telephone number that must be preordered in order to obtain all other associated telephone numbers.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	R	P	P	P	P	P
	C/INP	P	P	P	P	R	P	P	P	P	P

NOTE 1: This field is supported for manual processing only.

DATA CHARACTERISTICS: 10 numeric characters (excluding 2 preprinted hyphens)

EXAMPLE:

2	0	1
---	---	---

 -

5	5	5
---	---	---

 -

1	2	1	2
---	---	---	---

4. ATN - Account Telephone Number

Identifies the account telephone number assigned by the NSP.

Interface	Field Name
IRES	Not Applicable
FTP	Not Applicable

NOTE 1: This field describes all telephone numbers associated with the AN field.

NOTE 2: All numbers requesting migration must be supplied.

NOTE 3: When processing manually, each telephone number must be listed on a separate form.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	R	P	P	P	P	P
	C/INP	P	P	R	P	R	P	P	P	P	P

DATA CHARACTERISTICS: 10 numeric characters (excluding 2 preprinted hyphens)

EXAMPLE:

2	0	1
---	---	---

 -

5	5	5
---	---	---

 -

1	2	1	2
---	---	---	---

5. NPQTY - Number Portability Quantity

Identifies the quantity of ported numbers involved in this service request.

Interface	Field Name
IRES	NP QTY
FTP	NPQTY

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	R	P	P	P	P	P
	C/INP	P	P	R	P	R	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: Depending on REQ/ACT combination, field may be auto-populated in IRES.

DATA CHARACTERISTICS: 4 numeric characters

EXAMPLES:

				1
--	--	--	--	---

6. PG_of_ - Page _ of _

Identifies the page number and total number of pages contained in this request.

Interface	Field Name
IRES	Not Applicable
FTP	Not Applicable

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	R	P	P	P	P	P
	C/INP	P	P	R	P	R	P	P	P	P	P

DATA CHARACTERISTICS: 4 numeric characters

EXAMPLE: PG 1 of 2

5.3 NUMBER PORTABILITY SERVICE DETAILS SECTION

7. LOCNUM - Location Number

Identifies the service location number for the service requested.

USAGE: This field is not supported by Sprint LTD.

8. LNUM - Line Number

Identifies the line or trunk as a unique number and each additional occurrence as a unique number.

Interface	Field Name
IRES	LNUM
FTP	Not Applicable

NOTE 1: The LNUM is customer assigned for manual requests and is returned on the Local Response (LR) Form to the ordering customer.

NOTE 2: Once LNUM is assigned manually, it may be changed by Sprint LTD.

USAGE: See usage strip below.

ACTIVITIES											
REQ		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	R	P	P	P	P	P
	C/INP	P	P	R	P	R	P	P	P	P	P

NOTE 1: Field is auto-populated in IRES based on telephone numbers preordered.

DATA CHARACTERISTICS: 4 numeric characters

EXAMPLE:

0	0	0	1
---	---	---	---

9. NPI - Number Portability Indicator

Identifies the status of the telephone number being ported.

USAGE: This field is not supported by Sprint LTD.

10. LNA - Line Activity

Identifies the activity involved at the line level.

Interface	Field Name
IRES	LNA
FTP	NPLNA

VALID ENTRIES:

- B = Restore
- C = Change an existing account, e.g., rearrangement, partial disconnect or addition
- D = Disconnection
- H = Short term
- L = Seasonal
- M = Inside move of the physical termination within a building
- N = New installation and/or account
- P = PIC change
- R = Record activity is for ordering administrative changes
- S = Suspend
- T = Outside move of end user location
- V = Conversion of service to new LSP as specified
- W = Conversion as is
- X = Telephone number change
- Y = Deny

NOTE 1: “B”, “C”, “D”, “H”, “L”, “M”, “N”, “P”, “R”, “S”, “T”, “W”, “X” and “Y” are not supported by Sprint LTD for NP/LNP.

NOTE 2: “B”, “C”, “H”, “L”, “M”, “N”, “P”, “R”, “S”, “T”, “W”, “X” and “Y” are not supported by Sprint LTD for NP/INP.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	R	P	P	P	P	P
	C/INP	P	P	R	P	R	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE:

N

11. RL – Reuse Loop

Identifies the desire to reuse the loop from an existing service arrangement for this request.

USAGE: This field is not supported by Sprint LTD.

12. CKR - Customer Circuit Reference

Identifies the circuit number or sequential range of circuit numbers assigned by the customer.

USAGE: This field is not supported by Sprint LTD.

13. LRN - Location Routing Number

Identifies a number used to uniquely identify a switch that has ported numbers and is used to route a call to the switch that owns the NPA-NXX portion of the LRN.

Interface	Field Name
IRES	LRN
FTP	Not Applicable

USAGE: This field is not supported by Sprint LTD.

NOTE 1: This field appears in IRES, but currently is not supported.

14. TDT - Ten Digit Trigger

Indicates the request for the activation of a ten digit trigger for local routing number portability.

Interface	Field Name
IRES	TDT
FTP	TDT

NOTE 1: When ten digit trigger is requested, the request for the number port will occur at 11 p.m.

VALID ENTRIES:

Y = Yes

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	O	P	P	P	P	P
	C/INP	P	P	P	P	P	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: When this field usage is conditional (C), it will be prohibited if TDT field is populated, otherwise optional.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE:

15. ECCKT - Exchange Company Circuit ID

Identifies a provider's circuit identification.

USAGE: This field is not supported by Sprint LTD.

16. OECCKT – Out Exchange Company Circuit ID

Identifies the circuit identification that was previously provided to the old LSP/NSP-Switch by the NSP-Loop.

USAGE: This field is not supported by Sprint LTD.

17. PORTED NBR - Ported Telephone Number

Identifies the Telephone Number (TN) or consecutive range of TNs residing in the same switch to be ported.

Interface	Field Name
IRES	PORTED #
FTP	PORTEDNBR

NOTE 1: A single telephone number that is to be ported.

NOTE 2: This telephone number may be a customer or Sprint LTD number.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	R	P	P	P	P	P
	C/INP	P	P	R	P	R	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: When ACT=D for C/INP, this field will contain a customer telephone number.

NOTE 3: This field will be auto-populated in IRES based on preorder information.

DATA CHARACTERISTICS: 10 numeric characters (excluding 2 preprinted hyphens)

EXAMPLES: |9|0|8| - |6|9|9| - |7|0|0|0|

18. TNP - Total Number of Paths

Identifies the total number of talk paths, including the initial path, associated with the ported number.

Interface	Field Name
IRES	TNP
FTP	TNP

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	P	P	P	P	P	P
	C/INP	P	P	O	P	R	P	P	P	P	P

NOTE 1: Required when the LNA field is "V" and the NPT field is "B", otherwise optional.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

DATA CHARACTERISTICS: 3 numeric characters

EXAMPLE:

0	0	1
---	---	---

19. CFTN - Call Forward To Number

Identifies the telephone number to which calls will be directed.

Interface	Field Name
IRES	CFTN
FTP	CFTN

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	P	P	P	P	P	P
	C/INP	P	P	O	P	R	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

DATA CHARACTERISTICS: 10 numeric characters (excluding 2 pre-populated hyphens).

EXAMPLES: | 9 | 1 | 3 | - | 7 | 9 | 4 | - | 9 | 9 | 9 | 9 |

20. NPT - Number Portability Type

Indicates the type of number portability for this request.

Interface	Field Name
IRES	NPT
FTP	Not Applicable

VALID ENTRIES:

- A = DID
- B = RCF (INP)
- C = Route index
- D = Local Number Portability

NOTE 1: “A” and “C” are not supported by Sprint LTD.

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	C/LNP	P	P	P	P	R	P	P	P	P	P	P
	C/INP	P	P	O	P	R	P	P	P	P	P	P

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE: A

21. RTI - Route Index

Identifies the routing index to be used by Sprint LTD's switching equipment to forward/port Sprint LTD's telephone number to the customer's non-RCF trunk group.

USAGE: This field is not supported by Sprint LTD.

22. NPTG - Number Portability Trunk Group

Identifies the Two Six Code (TSC) of a dedicated trunk group, from the porting switch to the customer's Point Of Interface (POI), used to complete NP calls.

USAGE: This field is not supported by Sprint LTD.

23. LSCP – Local Service Provider Change Prohibited

Identifies that the end user has requested the option of prohibiting the change of their current service provider or removing the option.

USAGE: This field is not supported by Sprint LTD.

24. BA - Blocking Activity

Indicates the activity for the blocking of calls.

USAGE: This field is not supported by Sprint LTD.

25. BLOCK - Block

Identifies the type of blocking on the telephone number.

USAGE: This field is not supported by Sprint LTD.

26. FPI - Freeze PIC Indicator

Indicates the customer's requested freeze option.

USAGE: This field is not supported by Sprint LTD.

27. LPIC – IntraLATA Pre-subscription Indicator Code

Identifies the Pre-subscription Indicator Code (PIC) of the carrier the customer has selected for IntraLATA traffic.

USAGE: This field is not supported by Sprint LTD.

28. TC OPT - Transfer of Call Options

Identifies the type of transfer of call option the end user has requested.

Interface	Field Name
IRES	TC OPT
FTP	TCOPT

USAGE: See Section 3 - End User.

29. TC TO PRI - Transfer of Calls To Primary Number

Identifies the telephone number to which calls are to be referred.

Interface	Field Name
IRES	TC TO PRI
FTP	TCTOPRI

USAGE: Refer to Section 3 - End User.

30. TC TO SEC - Transfer of Calls To Secondary Number

Identifies the secondary telephone number to which calls are to be referred.

USAGE: This field is not supported by Sprint LTD.

31. TCID - Transfer of Calls To Identifier

Identifies the sequence of telephone numbers and names associated with split transfer of calls.

USAGE: This field is not supported by Sprint LTD.

32. TC NAME - Transfer of Calls To Name

Identifies the name(s) associated with TC TO PRI and TC TO SEC fields to which calls are to be referred when split transfer of calls is requested.

USAGE: This field is not supported by Sprint LTD.

33. TC PER - Transfer of Calls Period

Indicates the requested date that the transfer of calls, specified in the TC TO PRI field, is to be removed and the standard recorded announcement is to be provided.

Interface	Field Name
IRES	TC PER
FTP	TCPER

USAGE: See Section 3 - End User.

34. LEAN - Line Existing Account Number

Identifies the end user's existing account number assigned by the current NSP and/or LSP.

USAGE: This field is not supported by Sprint LTD.

35. LEATN - Line Existing Account Telephone Number

Identifies the end user's existing account telephone number assigned by the Sprint LTD.

USAGE: This field is not supported by Sprint LTD.

37. SOE REMARKS – SOE Remarks

Identifies information that is to be written directly to the service order (SOE).

Interface	Field Name
IRES	SOE REMARKS
FTP	Not Applicable

NOTE 1: This is Sprint LTD proprietary field.

NOTE 2: The purpose of this field is to allow users to provide information such as driving directions, can be reached numbers and rotary hunt sequences.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	C/LNP	P	P	P	P	R	P	P	P	P	P
	C/INP	P	P	O	P	R	P	P	P	P	P

DATA CHARACTERISTICS: 50 alphanumeric characters

EXAMPLE: N | W | | C | O | R | N | E | R | | O | F | | 5 | T | H | | & | | S |
 | A | N | T | A | | F | E | | B | L | V | D | . | | B | E | H | I | N | D |
 | | T | H | E | | P | I | Z | Z | A | | S | H | O | P | | | | |