

Table of Contents

9.	CENTREX _____	3
9.1	INTRODUCTION _____	3
9.2	CENTREX ADMINISTRATIVE SECTION _____	4
1.	PON - Purchase Order Number _____	4
2.	VER - Version Identification _____	5
3.	RSQTY - Resale Quantity _____	6
4.	ORD - Order Number _____	7
5.	ATN - Account Telephone Number _____	8
6.	AN – Account Number _____	9
7.	CB - Common Block _____	10
8.	PG_of_ - Page _ of _ _____	11
9.3	CENTREX COMMON BLOCK DETAILS _____	12
9.	SN - Station Numbers _____	12
10.	APS - Attendant Position _____	13
11.	SDD - Station Digit Dialing _____	14
12.	SMDR - Station Message Detail Recording _____	16
13.	SMDRAC - SMDR Account Code _____	17
14.	CPIC - Common Block InterLATA Pre-subscription Indicator Code _____	18
15.	CLPIC - Common Block IntraLATA Pre-subscription Indicator Code _____	19
16.	CIPIC - Common Block International Pre-subscription Indicator Code _____	20
17.	OAR - Operator Assisted Routing _____	21
18.	TA - Treatment Code Activity _____	22
19.	TMTC - Treatment Code _____	23
20.	CBA – Centrex Blocking Activity _____	24
21.	CBLOCK - CENTREX Common Block Restrictions _____	25
22.	DIALING - Dialing _____	26
23.	CPATH - CENTREX Access Paths _____	27
24.	CPATHA - CENTREX Access Paths Additional _____	28
25.	CFPI - CENTREX Common Block Freeze PIC Indicator _____	29
26.	LSCP - Local Service Provider Change Prohibited _____	30
27.	CBFA - Common Block Feature Activity _____	31
28.	CB FEATURE - Common Block Feature Codes _____	32
29.	CB FEATURE DETAIL - Common Block Feature Detail _____	33
9.4	CENTREX STATION DETAILS _____	34
30.	LOCNUM - Location Number _____	34
31.	LNUM - Line Number _____	35
32.	NPI - Number Portability Indicator _____	36
33.	LNA - Line Activity _____	38
34.	SOE - Service or Equipment Indicator _____	40
35.	NOTYP - Number Type _____	41
36.	TNS - Telephone Numbers _____	43
37.	RL – Reuse Loop _____	45
38.	OECKKT – Out Exchange Company Circuit ID _____	46
39.	TERS - Terminal Numbers _____	47
40.	API - Attendant Position Indicator _____	48
41.	OTN - Out Telephone Number _____	49

42.	CPG – Call Pickup Group	50
43.	SCPG – Secondary Call Pickup Group	51
44.	DSN - Dialable Station Number	52
45.	CLN - CENTREX Line Name	53
46.	PIC - InterLATA Pre-subscription Indicator Code	54
47.	LPIC - IntraLATA Pre-subscription Indicator Code	55
48.	IPIC - International Pre-subscription Indicator Code	56
49.	LTC - Line Treatment Code	57
50.	LSCP - Local Service Provider Change Prohibited	58
51.	BA - Blocking Activity	59
52.	BLOCK - Block	60
53.	CC-ACT - Calling Card Activity	62
54.	CC-NO - Calling Card Number	63
55.	CCT - Calling Card Type	64
56.	FLI - Foreign Language Indicator	65
57.	DI – Disability Indicator	66
58.	CKR - Customer Circuit Reference	67
59.	TSP - Telecommunications Service Priority	68
60.	SAN - Subscriber Authorization Number	69
61.	LEAN - Line Existing Account Number	70
62.	LEATN - Line Existing Account Telephone Number	71
63.	FPI - Freeze PIC Indicator	72
64.	BSPRAO – Billing Service Provider Revenue Accounting Office Code	73
65.	SGNL - Signaling	74
66.	SSIG - Start Signaling	75
67.	PULSE - Type of Pulsing	76
68.	JR - Jack Request	77
69.	JK CODE - Jack Code	78
70.	JK NUM - Jack Number	79
71.	JK POS - Jack Position	80
72.	IWJK - Inside Wire Jack Code	81
73.	IWT - Inside Wire Type	82
74.	IWJQ - Inside Wire Jack Quantity	83
75.	FA - Feature Activity	84
76.	FEATURE - Feature Codes	85
77.	FEATURE DETAIL - Feature Detail	86
78.	LD – Long Distance	87
79.	# PATHS – Number of Paths	88
80.	# RINGS – Number of RINGS	89
81.	REMARKS - Remarks	90
82.	SOE REMARKS – SOE Remarks	91

9. CENTREX

9.1 INTRODUCTION

1. This guide describes the CENTREX Resale Service (CRS) Ordering Form entries. The CRS Form must always be associated with an administrative Local Service Request (LSR) Form and an End User (EU) Form.

9.2 CENTREX ADMINISTRATIVE SECTION

1. PON - Purchase Order Number

Identifies the customer's unique purchase order or requisition number that authorizes the issuance of this request or supplement.

INTERFACE	Field Name
IRES	PON
FTP	PON

NOTE 1: The purchase order number can not be reused.

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	R	R	R	R	R	R	R	R	R	P	P
	M	R	R	R	R	R	R	P	R	R	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 16 alphanumeric characters

EXAMPLE: | 8 | 2 | 4 | Z | 9 | | | | | | | | | | | | | |

2. VER - Version Identification

Identifies the customer's version number.

Interface	Field Name
IRES	VER
FTP	Not applicable

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	R	R	R	R	R	P	P	P	P	P
	M	R	R	R	R	R	P	P	P	P	P

NOTE 1: The VER is auto-populated by IRES.

NOTE 2: IRES will increment the VER field by 1 when a SUP is submitted.

DATA CHARACTERISTICS: 2 alphanumeric characters

EXAMPLES: | A | A |

| A | 1 |

| 8 | |

3. RSQTY - Resale Quantity

Identifies the quantity of resale services (e.g., lines, circuits, trunks, etc.) involved in this service request.

Interface	Field Name
IRES	QTY
FTP	RSQTY

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	R	R	R	R	R	R	R	R	P	P
	M	R	R	R	R	R	P	R	R	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: Depending on REQ/ACT combination, field may be auto-populated in IRES.

DATA CHARACTERISTICS: 5 numeric characters

EXAMPLE:

			8	5
--	--	--	---	---

4. ORD - Order Number

Identifies the provider's order number for the service requested.

USAGE: This field is not supported by Sprint LTD.

5. ATN - Account Telephone Number

Identifies the account telephone number assigned by the NSP.

Interface	Field Name
IRES	TEL NO
FTP	TN

NOTE 1: This field describes all telephone numbers associated with the AN field.

NOTE 2: All numbers requesting migration must be supplied.

NOTE 3: When processing manually, each telephone number must be listed on a separate form.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	R	R	R	R	R	R	R	R	P	P
	M	R	R	R	R	R	P	R	R	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

NOTE 2: Field will be auto-populated in IRES based on preorder information.

DATA CHARACTERISTICS: 10 alphanumeric characters (excluding 2 preprinted hyphens)

EXAMPLE: | 4 | 1 | 5 | - | 3 | 5 | 4 | - | 1 | 2 | 3 | 4 |

| N | | | - | | | | - | | | |

6. AN – Account Number

Identifies the main account number assigned by the NSP.

Interface	Field Name
IRES	Not Applicable
FTP	Not Applicable

NOTE 1: This field is the Sprint LTD end users main telephone number assigned by Sprint LTD and represents an account that has not been migrated to another customer.

NOTE 2: This field is used to recognize the main telephone number that must be preordered in order to obtain all other associated telephone numbers.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	R	R	R	R	R	R	R	R	P	P
	M	R	R	R	R	R	P	R	R	P	P

NOTE 1: Field is only supported for manual processing.

NOTE 2: When REQ TYPE = A and 2nd TOS = R, this field is required, otherwise prohibited.

DATA CHARACTERISTICS: 20 alphanumeric characters

EXAMPLES:

B	2	3	4	5	6														
A	B	3	2	2	1	4	7												
N																			

7. CB - Common Block

Identifies the name/number of the CENTREX and the name/number of the grouping (customer common block).

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: There can only be one common block per CRS Form.

NOTE 2: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
REQ		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

8. PG_of_ - Page _ of _

Identifies the page number and total number of pages contained in this request.

Interface	Field Name
IRES	Not Applicable
FTP	Not Applicable

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	R	R	R	R	R	R	R	R	R	P	P
	M	R	R	R	R	R	R	P	R	R	P	P

DATA CHARACTERISTICS: 6 numeric characters

EXAMPLE: PG 1 of 2

9.3 CENTREX COMMON BLOCK DETAILS

9. SN - Station Numbers

Identifies the station numbers or range of station numbers assigned to the CENTREX common block.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

10. APS - Attendant Position

Identifies the number of attendant positions for the CENTREX common block.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

11. SDD - Station Digit Dialing

Identifies the dialing patterns of the CENTREX common block.

Interface	Field Name
IRES	SDD
FTP	SDD

VALID ENTRIES:

POSITION ONE (1):

- # of digits = 1
- D = Disables station-to-station dialing

NOTE 1: The first alphanumeric character allows terminals to complete calls to other terminals, without the assistance of an attendant, by dialing a one through seven-digit number.

POSITION TWO (2):

- Prefix = 1
- N = No prefix (assume dial 9)

NOTE 1: The second alphanumeric character identifies the prefix for accessing the local network by dialing a single number.

NOTE 2: If the second character is N, then the third character must be N.

POSITION THREE (3):

- Prefix = 1
- N = No prefix (assume dial 9)

NOTE 1: The third alphanumeric character identifies the prefix for accessing a private facility, tie trunk or DAL by dialing a single number.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	R	R	P	R	R	R	R	R	P	P
	M	R	R	P	R	R	P	R	R	P	P

NOTE 1: Required when the ACT field on the LSR Form is “N” or “V”, otherwise optional.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 3 alphanumeric characters

EXAMPLES: | 4 | 9 | 8 |

| D | N | N |

| 7 | N | N |

12. SMDR - Station Message Detail Recording

Identifies that the SMDR call detail recording system is actuated on all calls placed by station users.

USAGE: This field is not supported by Sprint LTD.

13. SMDRAC - SMDR Account Code

Identifies the billing number to put into a Station Message Detail Recording (SMDR) record for charge-back purposes for the CENTREX common block.

USAGE: This field is not supported by Sprint LTD.

14. CPIC - Common Block InterLATA Pre-subscription Indicator Code

Identifies the Pre-subscription Indicator Code (PIC) of the carrier the customer has selected for all InterLATA traffic from this CENTREX common block.

USAGE: This field is not supported by Sprint LTD.

15. CLPIC - Common Block IntraLATA Pre-subscription Indicator Code

Identifies the Pre-subscription Indicator Code (PIC) of the carrier the customer has selected for all IntraLATA traffic from this CENTREX common block.

USAGE: This field is not supported by Sprint LTD.

16. CIPIC - Common Block International Pre-subscription Indicator Code

Identifies the Pre-subscription Indicator Code (PIC) of the carrier that the customer has selected for International traffic from this CENTREX common block.

USAGE: This field is not supported Sprint LTD.

17. OAR - Operator Assisted Routing

Identifies a requirement for custom routing of 0+ local, 0-, 411 or 555-1212 calls.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

18. TA - Treatment Code Activity

Indicates the activity type for the treatment code associated with the CENTREX common block.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

19. TMTC - Treatment Code

Identifies the unique treatment profile code required for the CENTREX common block.

NOTE 1: Code is for associating profiles with lines.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

20. CBA – Centrex Blocking Activity

Indicates the activity for the blocking of calls at the CENTREX common block.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

21. CBLOCK - CENTREX Common Block Restrictions

Identifies the type of blocking on the CENTREX common block.

NOTE 1: If individual line restrictions are allowed in the CENTREX common block, they must be specified in the BLOCK field in the Station Details section.

USAGE: This field is not supported by Sprint LTD.

22. DIALING - Dialing

Identifies CENTREX dialing capability.

Interface	Field Name
IRES	DIALING
FTP	DIALING

VALID ENTRIES:

- A = DID - Direct inward dialing
- B = DOD - Direct outward dialing
- C = AIOD - Automatic inward/outward dialing
- D = DISA - Direct inward station access
- E = Combination of A and B
- F = Combination of B and D

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when the ACT field on the LSR Form is “N” or “V”, otherwise optional.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE: A

23. CPATH - CENTREX Access Paths

Identifies the quantity of access paths associated with the CENTREX common block.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

24. CPATHA - CENTREX Access Paths Additional

Identifies the additional quantity of access paths associated with the CENTREX common block.

NOTE 1: This quantity is in addition to the CPATH field quantities provided, based on line size.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

25. CFPI - CENTREX Common Block Freeze PIC Indicator

Indicates the customer's requested freeze option for the CPIC or CLPIC fields.

USAGE: This field is not supported by Sprint LTD.

26. LSCP - Local Service Provider Change Prohibited

Identifies that the end user has requested the option of prohibiting the change of their current service provider or removing the option.

Interface	Field Name
IRES	S&E CODE
FTP	FEATURE

NOTE 1: Invoking this option may require additional authorization or written permission.

NOTE 2: This code is used to only freeze the requested line.

NOTE 3: In IRES, the S&E Code can be found in the MISC Category on the Line Detail Tab.

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	O	O	P	O	O	P	P	P	P	P	P
	M	O	O	P	O	O	P	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE: A

27. CBFA - Common Block Feature Activity

Identifies the activity type for the feature, or package of features, associated with the CENTREX common block.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

28. CB FEATURE - Common Block Feature Codes

Identifies the type of feature, or package of features, associated with the CENTREX common block.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

29. CB FEATURE DETAIL - Common Block Feature Detail

Identifies additional information for the type of feature, or package of features, associated with the CENTREX common block.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

9.4 CENTREX STATION DETAILS

30. LOCNUM - Location Number

Identifies the service location number for the service requested.

USAGE: This field is not supported by Sprint LTD.

31. LNUM - Line Number

Identifies the line or trunk as a unique number and each additional occurrence as a unique number.

Interface	Field Name
IRES	Not Applicable
FTP	Not Applicable

NOTE 1: The LNUM is customer assigned for manual requests and is returned on the Local Response (LR) Form to the ordering customer.

NOTE 2: Once LNUM is assigned manually, it may be changed by Sprint LTD.

NOTE 3: This field is not supported for IRES or FTP.

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	R	R	R	R	R	R	R	R	R	P	P
	M	R	R	R	R	R	R	P	R	R	P	P

DATA CHARACTERISTICS: 5 numeric characters

EXAMPLE: | 0 | 0 | 0 | 0 | 1 |

32. NPI - Number Portability Indicator

Identifies the status of the telephone number being ported.

Interface	Field Name
IRES	NPI
FTP	NPI

VALID ENTRIES:

- A = Port out reserved TN
- B = Port out working TN
- C = Port in working TN
- D = Port in reserved TN
- E = Port in wireless TN

NOTE 1: Reserved numbers can only be ported when associated with an active account.

NOTE 2: “C” is the only valid entries for this section.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E	P	O	O	P	C	C	P	P	P	P	P
Q	M	O	O	P	C	C	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: When REQ TYP=E or M and ACT=N, the end user customer may port in a number. The DDD field must have a date that is concurrent with the date of the disconnect where that line number currently resides.

NOTE 3: When REQ TYP=E or M and ACT = T and the end user existing wire center is changing the line number can be ported with a valid value of “C.”

NOTE 4: When REQ TYP = E or M and ACT= V and the EUMI = Y and the end user existing wire center is changing the line number can be ported with a valid value of “C.”

NOTE 5: When NPI field is populated, all associated line numbers must also have the same NPI value.

NOTE 6: The telephone number must be within the disconnect period or it will be returned to the available number pool.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE:

A

33. LNA - Line Activity

Identifies the activity involved at the line level.

Interface	Field Name
IRES	LNA
FTP	RLNA

VALID ENTRIES:

- B = Restore
- C = Change an existing account, e.g., rearrangement, partial disconnect or addition
- D = Disconnection
- H = Short term
- L = Seasonal
- M = Inside move
- N = New installation and/or account
- P = PIC change
- R = Record activity is for ordering administrative changes
- S = Suspend
- T = Outside move
- V = Conversion of service to new LSP as specified
- W = Conversion as is
- X = Telephone number change
- Y = Deny

NOTE 1: “H”, “M”, and “Y” are not supported by Sprint LTD.

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	R	R	R	R	R	R	R	R	R	P	P
	M	R	R	R	R	R	R	P	R	R	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: When ACT=V, valid LNA values are “N”, “W” or “V.”

NOTE 3: When ACT = N, valid LNA value is “N.”

NOTE 4: When ACT = C, valid LNA values are “C, X, P & L

NOTE 5: When ACT=D, valid LNA value is “D.”

NOTE 6: When ACT=T, valid LNA value is “T.”

NOTE 7: When ACT=L, valid LNA value is “L.”

NOTE 8: When ACT =B, valid LNA value is “B.”

NOTE 9: When ACT=S, valid LNA value is “S.”

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE:

N

34. SOE - Service or Equipment Indicator

This field identifies the type of service/equipment associated with the line in the LIDB.

USAGE: This field is not supported by Sprint LTD.

35. NOTYP - Number Type

Identifies the type of telephone number.

NOTE 1: Identifies the type of telephone number entered in the TNS or OTN fields.

VALID ENTRIES:

- B ISDN BRI directory number
- L Terminal number
- M Maintenance number
- R Line number
- T Telephone number
- MCA Metro Calling Area
- TNBR Total number service
- MEXT Message line extension
- REG Coin, Centrex Numbers, Int Switch dig Network, Regular, Test, Company Official Nm, Out Watts, 800service, Customer own phone, PATS, Paging, Cellular, Wireless
- MBEX Military base extensions
- MSGL Message line number
- STGV State Government numbers
- MBAS Military Base

NOTE 1: “B”, “L” “M”, “R” and “T” are not supported Sprint LTD.

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	C	C	P	C	C	P	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P	P

NOTE 1: When LNA = N or X, new telephone number(s) must be assigned.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 3: Required when the TNS field or OTN field is populated, otherwise prohibited.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE:

T

36. TNS - Telephone Numbers

Identifies the telephone number or consecutive range of telephone numbers for this request.

Interface	Field Name
IRES	CLEC Remark Tab
FTP	RWTN

NOTE 1: All telephone numbers for this request must be within the same switch.

NOTE 2: All telephone numbers associated with a range must have the same NPA/NXX.

NOTE 3: When ranging line numbers, a hyphen must be used as a delimiter.

VALID ENTRIES:

N = New telephone number requested
 EOP = Extension off premises

XXX-XXX-XXXX = Telephone Number example below
 ISDN telephone number(s)
 Maintenance number
 Telephone number(s)
 Terminal number(s)

NOTE 1: ISDN telephone number(s) is not valid for this section.

NOTE 2: When the LNA field is “X”, the entry in this field indicates the new telephone number or request for a new telephone number. The out telephone number is shown in the OTN field.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when the LNA field is populated, otherwise optional.

NOTE 2: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 15 alphanumeric characters (excluding 2 preprinted hyphens)

EXAMPLES:

2	0	1
---	---	---

 -

6	9	9
---	---	---

 -

0	0	0	1				
---	---	---	---	--	--	--	--

9	0	8
---	---	---

 -

5	5	5
---	---	---

 -

1	0	0	0
---	---	---	---

 -

1	9	9	9
---	---	---	---

37. RL – Reuse Loop

Identifies the desire to reuse the loop from an existing service arrangement for this request.

USAGE: This field is not supported by Sprint LTD.

38. OECCKT – Out Exchange Company Circuit ID

Identifies the circuit identification that was previously provided to the old LSP/NSP-Switch by the NSP-Loop.

USAGE: This field is not supported by Sprint LTD.

39. TERS - Terminal Numbers

Identifies the number for a non-lead line in a multiline hunt group or consecutive range of terminal numbers.

USAGE: This field is not supported by Sprint LTD.

40. API - Attendant Position Indicator

Indicates if this line is an attendant position.

USAGE: This field is not supported by Sprint LTD.

41. OTN - Out Telephone Number

Identifies the existing telephone number that is being changed.

Interface	Field Name
IRES	OTN
FTP	OTN

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	P	P	P	C	C	P	P	P	P	P
	M	P	P	P	C	C	P	P	P	P	P

NOTE 1: Required when the LNA field is "X".

NOTE 2: Optional when the LNA field is "T".

NOTE 3: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 10 numeric characters (excluding 2 preprinted hyphens)

EXAMPLE:

2	0	1
---	---	---

 -

6	9	9
---	---	---

 -

0	0	0	1
---	---	---	---

42. CPG – Call Pickup Group

Indicates

USAGE: This field is not supported by Sprint LTD.

43. SCPG – Secondary Call Pickup Group

Indicates

USAGE: This field is not supported by Sprint LTD.

44. DSN - Dialable Station Number

Identifies the dialable one to seven (1-7) digit station digit dialing number.

USAGE: This field is not supported by Sprint LTD.

45. CLN - CENTREX Line Name

Identifies the name associated with the CENTREX line for optional display associated with CENTREX station-to-station dialing.

USAGE: This field is not supported by Sprint LTD.

46. PIC - InterLATA Pre-subscription Indicator Code

Identifies the Pre-subscription Indicator Code (PIC) of the carrier the customer has selected for InterLATA traffic.

Interface	Field Name
IRES	PIC
FTP	PIC

VALID ENTRIES:

Valid PIC code

NONE

NA = Not applicable

DFLT = Default

UNDC = Undecided

NC = No change

NOTE 1: NONE - Customer does not want to pre-subscribe.

NOTE 2: “NA”, “DFLT,” “NC,” and “UNDC” are not supported by Sprint LTD.

USAGE: See usage strip below.

ACTIVITIES											
R		N	C	D	T	V	W	S	B	L	P
E	P	R	C	P	C	C	P	P	P	P	P
Q	M	R	C	P	C	C	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

NOTE 2: Required when the LNA field is “N”, or “P”, otherwise optional.

NOTE 3: Optional when LNA field is “C” or “X”.

DATA CHARACTERISTICS: 4 alphanumeric characters

EXAMPLE:

0	2	2	2
---	---	---	---

47. LPIC - IntraLATA Pre-subscription Indicator Code

Identifies the Pre-subscription Indicator Code (PIC) of the carrier the customer has selected for IntraLATA traffic.

Interface	Field Name
IRES	LPIC
FTP	LPIC

VALID ENTRIES:

Valid PIC code
 NONE
 NA = Not applicable
 DFLT = Default
 UNDC = Undecided
 NC = No change

NOTE 1: NONE - Customer does not want to pre-subscribe.

NOTE 2: “NA,” “DFLT,” “NC” and “UNDC” are not supported by Sprint LTD.

USAGE: This field is conditional.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	R	C	P	C	C	P	P	P	P	P
	M	R	C	P	C	C	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

NOTE 2: Required when the LNA field is “N”, or “P”, otherwise optional.

NOTE 3: Optional when LNA field is “C” or “X”.

DATA CHARACTERISTICS: 4 alphanumeric characters

EXAMPLE:

0	2	2	2
---	---	---	---

48. IPIC - International Pre-subscription Indicator Code

Identifies the Pre-subscription Indicator Code (PIC) of the carrier the customer has selected for international traffic.

USAGE: This field is not supported by Sprint LTD.

49. LTC - Line Treatment Code

Identifies the unique treatment profile code required for this line when the CENTREX common block contains more than one treatment code.

NOTE 1: Code is for associating profiles with lines.

Interface	Field Name
IRES	INFORMATION Pop-up Box
FTP	Not Applicable

NOTE 1: There can only be one common block per CRS Form.

NOTE 2: Sprint LTD does not support entries in this field, but instead supports a manual fax process of common block data.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	C	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: Required when specific end user equipment (Meridian) needs exist.

50. LSCP - Local Service Provider Change Prohibited

Identifies that the end user has requested the option of prohibiting the change of their current service provider or removing the option.

Interface	Field Name
IRES	S&E CODE
FTP	FEATURE

NOTE 1: Invoking this option may require additional authorization or written permission.

NOTE 2: This code is used to only freeze the requested line.

NOTE 3: In IRES, the S&E Code can be found in the MISC Category on the Line Detail Tab.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	O	O	P	O	O	P	P	P	P	P
	M	O	O	P	O	O	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE: A

51. BA - Blocking Activity

Indicates the activity for the blocking of calls.

Interface	Field Name
IRES	Not Applicable
FTP	BA

VALID ENTRIES:

- A = Add
- D = Delete
- N = No change
- Z = Remove all blocking

USAGE: See usage strip below

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	O	O	P	O	O	P	P	P	P	P	P
	M	O	O	P	O	O	P	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE: D

52. BLOCK - Block

Identifies the type of blocking on the telephone number.

Interface	Field Name
IRES	S&E CODE
FTP	BLOCK

NOTE 1: If populated, line entries supersede CENTREX common block restrictions.

VALID ENTRIES:

- A = No collect and third party
- B = No third party
- C = No collect call
- D = No 1+
- E = No 0+ local
- F = No 1+ and 0+ local
- G = No 011 (international)
- H = No Directory Assistance Call Completion (DACC)
- J = No 700
- K = No 976
- L = No 915
- M = No 900
- N = No casual calling
- P = No N11 (except 911 and 411)
- Q = No 411
- R = No incoming (CENTREX)
- S = No 976, 900-303, 900-505
- T = No 900-303
- U = No IntraLATA toll
- V = No InterLATA toll
- W = No 7 digit toll (CENTREX)
- X = No national directory assistance
- Y = No 500
- Z = All
- 1 = Life line

NOTE 1: Valid Entry of “Z” may not include the same types of blocking by all providers.

NOTE 2: Entries listed above are not supported for IRES or manual processing.

NOTE 3: See usage notes below for FTP processing.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: State Tariff specific.

53. CC-ACT - Calling Card Activity

Identifies the activity involved for the calling card number.

USAGE: This field is not supported by Sprint LTD.

54. CC-NO - Calling Card Number

Identifies the calling card number for this request.

USAGE: This field is not supported by Sprint LTD.

55. CCT - Calling Card Type

Identifies the type of restriction associated with the calling card for this request.

USAGE: This field is not supported by Sprint LTD.

56. FLI - Foreign Language Indicator

Identifies the foreign language preference associated with the line number.

USAGE: This field is not supported by Sprint LTD.

57. DI – Disability Indicator

Identifies for LIDB that the end user has a disability that requires special handling of operator assisted and/or directory-assistance calls.

USAGE: This field is not supported by Sprint LTD.

59. TSP - Telecommunications Service Priority

Indicates the provisioning and restoration priority as defined under the TSP Service Vendor Handbook.

Interface	Field Name
IRES	TSP
FTP	TSP

NOTE 1: These codes are assigned by the TSP Program Office.

VALID ENTRIES:

- Nine character TSP control identifier
- One character provisioning priority level (E, 0 - 5)
- One digit restoration priority level (0 - 5)

NOTE 1: A TSP code ending in “00” indicates revocation, the removal of a previously assigned TSP code.

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	O	O	P	O	O	P	P	P	P	P	P
	M	O	O	P	O	O	P	P	P	P	P	P

DATA CHARACTERISTICS: 12 alphanumeric characters (including 1 hyphen)

EXAMPLE: | T | S | P | 1 | 2 | 3 | 4 | 5 | C | - | E | 1 |

60. SAN - Subscriber Authorization Number

Identifies a number equivalent to the end user purchase order number.

USAGE: This field is not supported by Sprint LTD.

61. LEAN - Line Existing Account Number

Identifies the end user's existing account number assigned by the current NSP and/or LSP.

USAGE: This field is not supported by Sprint LTD.

62. LEATN - Line Existing Account Telephone Number

Identifies the end user's existing account telephone number assigned by the old LSP.

USAGE: This field is not supported by Sprint LTD.

63. FPI - Freeze PIC Indicator

Identifies a request that PIC activity on the Working Telephone Number (WTN) be restricted.

Interface	Field Name
IRES	FPIC
FTP	FPIC

NOTE 1: This instance of the FPI field identifies the LSP end user’s freeze option for the PIC and LPIC fields.

VALID ENTRIES:

- A = Freeze LSP’s IntraLATA PIC
- B = Freeze LSP’s Inter & IntraLATA PIC
- E = Freeze LSP’s InterLATA PIC
- R = Remove InterLATA freeze
- S = Remove IntraLATA freeze
- T = Remove Inter & IntraLATA freezes

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	O	O	P	O	O	P	P	P	P	P
	M	O	O	P	O	O	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE: A

64. BSPRAO – Billing Service Provider Revenue Accounting Office Code

Identifies the Revenue Accounting Office (RAO) code that the Local Service Provider (LSP) has designated.

USAGE: This field is not supported by Sprint LTD.

65. SGNL - Signaling

Identifies the type of signaling requested.

Interface	Field Name
IRES	SGNL
FTP	SGNL

VALID ENTRIES:

- LP = Loop
- E1 = E + M1
- E2 = E + M2
- E3 = E + M3

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	C	C	P	C	C	P	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

NOTE 2: Value is optional when the 2nd TOS is equal to H, J or K, otherwise prohibited.

DATA CHARACTERISTICS: 2 alphanumeric characters

EXAMPLE: | L | P |

66. SSIG - Start Signaling

Identifies the type of start signaling requested.

Interface	Field Name
IRES	SSIG
FTP	SSIG

VALID ENTRIES:

- LS = Loop start
- GS = Ground start
- WS = Wink start
- DD = Delayed dial
- IM = Immediate dial

NOTE 1: Only entries of “LS” or “GS” are allowed when the SGNL field is “LP”.

NOTE 2: Only entries of “WS”, “DD” or “IM” are allowed when the SGNL field is “E1”, “E2” or “E3”.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

DATA CHARACTERISTICS: 2 alpha characters

EXAMPLE: | D | D |

67. PULSE - Type of Pulsing

Identifies the type of pulsing.

Interface	Field Name
IRES	PULSE
FTP	PULSE

VALID ENTRIES:

- DP = Dial pulse
- MF = Multi-frequency
- DTMF = Dual-tone multi-frequency

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	O	O	P	O	O	P	P	P	P	P	P
	M	O	O	P	O	O	P	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: When the 2nd TOS is equal to A, H, J or K field is optional, otherwise prohibited.

DATA CHARACTERISTICS: 4 alpha characters

EXAMPLE:

D	P		
---	---	--	--

68. JR - Jack Request

Indicates a request for a new jack.

USAGE: This field is not supported by Sprint LTD.

69. JK CODE - Jack Code

Indicates the standard code for the particular registered or non-registered jack used to terminate the service.

USAGE: This field is not supported by Sprint LTD.

70. JK NUM - Jack Number

Identifies the number of the jack used on end user connections.

USAGE: This field is not supported by Sprint LTD.

71. JK POS - Jack Position

Identifies the position in the jack that a particular service will occupy.

USAGE: This field is not supported by Sprint LTD.

72. IWJK - Inside Wire Jack Code

Indicates the standard code for the type of jack requested for inside wiring.

USAGE: This field is not supported by Sprint LTD.

73. IWT - Inside Wire Type

Identifies the type of inside wiring to be used.

USAGE: This field is not supported by Sprint LTD.

74. IWJQ - Inside Wire Jack Quantity

Indicates the number of jacks requested for inside wiring.

Interface	Field Name
IRES	JKQTY
FTP	IWJQ

NOTE 1: When multiple lines are terminating in one multi-line jack, the IWJQ field should only be populated for the first line. Jacks may be ordered on a line by line basis.

VALID ENTRIES:

01 – 99

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

NOTE 2: This field is optional when WIRE field is populated, otherwise prohibited.

DATA CHARACTERISTICS: 2 numeric characters

EXAMPLE:

0	1
---	---

75. FA - Feature Activity

Indicates the activity type for the feature.

Interface	Field Name
IRES	FA
FTP	FA

VALID ENTRIES:

- N = Add/install
- C = Change to feature detail
- D = Disconnect
- I = Insert listings/data
- O = Delete listings/data
- T = Outside Move
- V = Conversion to new LSP as specified
- W = Conversion as is

NOTE 1: “C”, “I” and “O” are not supported by IRES.

NOTE 2: “C”, “I”, “V”, “W” are not supported by FTP.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	R	O	P	O	O	O	P	P	P	P
	M	O	O	P	O	O	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: When ACT = N, C, T, V or W, IRES will auto-populate the FA field.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLE: D

76. FEATURE - Feature Codes

Identifies the type of feature associated with the line.

Interface	Field Name
IRES	S&E CODE
FTP	FEATURE

NOTE 1: Codes for feature identification may include USOCs, FIDs, company provided codes or TCIF maintained EDI codes.

NOTE 2: Sprint LTD uses this field to select the access line associated with the TOS/LTOS.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation

NOTE 2: Required when the FA field is populated, otherwise optional.

DATA CHARACTERISTICS: 3-13 alphanumeric characters

EXAMPLE: | 1 | F | L | C | | | | | | | | | |

77. FEATURE DETAIL - Feature Detail

Identifies additional information for the type of feature associated with the line.

Interface	Field Name
IRES	FEATURE DETAIL
FTP	Not Applicable

NOTE 1: This is a Sprint proprietary field and used in accordance with Industry standards.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

DATA CHARACTERISTICS: 22 alphanumeric characters including 2 pre-populated hyphens.

EXAMPLES:

9	1	3	-	1	2	3	-	4	5	6	7										
---	---	---	---	---	---	---	---	---	---	---	---	--	--	--	--	--	--	--	--	--	--

78. LD – Long Distance

Identifies if the telephone number associated with fixed call forward and remote call forward telephone number is to be dialed 1+.

Interface	Field Name
IRES	LD
FTP	Not Applicable

NOTE 1: This is a Sprint proprietary field and used in accordance with Industry standards.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	P	C	C	P	C	C	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: When REQ TYP = M the 4th TOS of “R” is prohibited.

DATA CHARACTERISTICS: 1 alpha character

EXAMPLES: Y

79. # PATHS – Number of Paths

Identifies the number of paths associated with remote call forwarding

Interface	Field Name
IRES	#PATHS
FTP	NUMOFPATHS

NOTE 1: This is a Sprint proprietary field and not supported by Industry.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	E	C	C	P	C	C	P	P	P	P	P
	D	P	P	P	P	P	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: Required when Feature Detail is populated.

DATA CHARACTERISTICS: 1-3 numeric characters

EXAMPLES:

3		
---	--	--

80. # RINGS – Number of RINGS

Identifies the number of rings needed when call forward no answer is selected.

Interface	Field Name
IRES	#RINGS
FTP	RINGS

NOTE 1: This is a Sprint proprietary field and not supported by Industry.

USAGE: See usage strip below.

ACTIVITIES											
R E Q		N	C	D	T	V	W	S	B	L	P
	E	C	C	P	C	C	P	P	P	P	P
	D	P	P	P	P	P	P	P	P	P	P
	M	C	C	P	C	C	P	P	P	P	P

NOTE 1: For usage related to FTP, refer to Sprint FTP SIBR and supporting documentation.

NOTE 2: Optional when FCD1FLC feature code is present.

NOTE 3: Value defaulted to 4 if not populated.

DATA CHARACTERISTICS: 10 numeric characters including 2 pre-populated hyphens

EXAMPLES:

9	1	3	-	1	2	3	-	4	5	6	7
---	---	---	---	---	---	---	---	---	---	---	---

82. SOE REMARKS – SOE Remarks

Identifies information that is to be written directly to the service order (SOE).

Interface	Field Name
IRES	SOE REMARKS
FTP	Not Applicable

NOTE 1: This is Sprint LTD proprietary field.

NOTE 2: The purpose of this field is to allow users to provide information such as driving directions, can be reached numbers and rotary hunt sequences.

USAGE: See usage strip below.

ACTIVITIES												
R E Q		N	C	D	T	V	W	S	B	L	P	
	P	O	O	O	O	O	O	O	O	O	O	P
	M	O	O	O	O	O	O	P	O	O	P	P

DATA CHARACTERISTICS: 50 alphanumeric characters

EXAMPLE: N | W | | C | O | R | N | E | R | | O | F | | 5 | T | H | | & | | S |
 | A | N | T | A | | F | E | | B | L | V | D | . | | B | E | H | I | N | D |
 | | T | H | E | | P | I | Z | Z | A | | S | H | O | P | | | | |